

Miniature One and Two-Channel RF Receivers

SK-910RAQ 3A relay output, 1 Channel

SK-910RAVQ Transistor Group O/P, 1 Channel

SK-910RAV2Q Transistor Group O/P, 2 Channel

Features:

- Four programmable output modes:
 - 4-Second Momentary Output
 - Validity Output
 - Toggle Output
 - 1-Second Momentary Output
- Flexible operating voltage:
 - SK-910RAQ: 11~24VAC/VDC
 - SK-910RAVQ / SK-910RAV2Q: 3~13.8 VDC
- Up to 500ft (152m) range*, 315MHz†
- Controls garage doors, gates, house lights, alarm panels, or other devices via remote
- Compatible with all 315MHz SECO-LARM transmitters (fixed code and CODEBUMP™)
- LED indicates RF reception, learn mode entered, transmitter learned, memory cleared, and relay output mode



SK-910RAQ



SK-910RAV2Q

4
Output modes

315MHz
Frequency

Small Size

Up to 500ft

Specifications:

Model	SK-910RAQ	SK-910RAVQ	SK-910RAV2Q
Operating frequency	315MHz		
Memory capacity	15 transmitter button codes per channel		
Operating voltage	11~24 VAC/VDC	3~13.8 VDC	
Range	Up to 500ft (152m)		
Current draw	Standby	5mA@12VDC	
	LED Flashing	50mA@12VDC	15mA@12VDC
Output mode	Programmable 4-sec. momentary (default), 1-sec. momentary, toggle (ON/OFF), or validity		
Output type	3A Form C relay (NO/NC/COM)	Transistor GND x 1, 5A@12VDC	Transistor GND x 2, 3A@12VDC
Dimensions	3 ³ / ₁₆ "x2 ⁹ / ₁₆ "x3 ³ / ₄ " (80x65x19 mm)		

Compatible Transmitters:

Model	315MHz		
	CODEBUMP™	68 Billion Codes	
	Pendant		Handheld
SK-910RAQ	SK-917T1-GBQ	SK-919T1-GBQ	SK-919TP1H-BQ
SK-910RAVQ	SK-917T1-GBUQ	SK-919T1-GBUQ	
SK-910RAV2Q	SK-917T2-GNQ	SK-919T2-GNQ	SK-919TP2H-NQ
	SK-917T3-GNQ	SK-919T3-GNQ	SK-919TP4H-NQ
	SK-917T4-GNQ	SK-919T4-GNQ	

*Operating range will vary greatly depending on the installation and operating environment.
 †433.92MHz Miniature RF Receivers also available by special order only. Contact SECO-LARM for more details.

SECO-LARM® U.S.A., Inc.

16842 Millikan Avenue, Irvine, CA 92606

Phone: (949) 261-2999 | (800) 662-0800 Fax: (949) 261-7326

Website: www.seco-larm.com Email: sales@seco-larm.com



Copyright © 2020 SECO-LARM U.S.A., Inc. All rights reserved.
 All trademarks are the property of SECO-LARM U.S.A., Inc. or their respective owners.
 The SECO-LARM policy is one of continual development. For that reason, SECO-LARM reserves the right to change prices and specifications without notice. SECO-LARM is not responsible for misprints.

SECO-LARM® ENFORCER® CRIMEBUSTER® CBA® SLI®

One and Two-Channel RF Receivers

- SK-910RBQ** 315MHz, 1 Channel
- SK-910RB2Q** 315MHz, 2 Channel
- SK-910R-4Q** 433.92MHz, 1 Channel
- SK-910RB2-4Q** 433.92MHz, 2 Channel

Features:

- Five programmable relay output modes:
 - 4-Second momentary
 - 1-Second momentary
 - Toggle (ON/OFF)
 - Validity
 - Latch†
- 11~24 VAC/VDC Operation
- Range: Up to 500ft (152m)*
- Controls garage doors, gates, house lights, alarm panels or other devices via remote
- LED indicates RF reception, learn mode entered, transmitter learned, memory cleared, and relay output mode
- Pushbutton programming, no need to cut jumpers†
- Up to 15 transmitter button codes can be learned



SK-910RBQ / SK-910R-4Q



SK-910RB2Q / SK-910RB2-4Q

5
Output
modes†

11~24
VAC/VDC

LED
Indicators

Up to
500ft

Specifications:

Model	SK-910RBQ	SK-910RB2Q	SK-910R-4Q	SK-910RB2-4Q
Operating frequency	315MHz		433.92MHz	
Memory capacity	15 transmitter button codes per channel			
Operating voltage	11~24 VAC/VDC			
Operating current	Standby	8mA@12VDC		
	Active	30mA@12VDC per channel		
Relay contact rating	Form C 10A@24VDC per channel			
Connectors	Screw terminals, +, -, with NO/NC/COM per channel			
Dimensions	3 1/8" x 2 9/16" x 1" (80x65x25 mm)		3 1/4" x 2 11/16" x 1 1/16" (83x68x27.5 mm)	

*Operating range will vary greatly depending on the installation and operating environment.
 † SK-910RBQ, SK-910RB2Q, and SK-910RB2-4Q only

Compatible Transmitters:

Model	315MHz		
	CODEBUMP™	68 Billion Codes	
	Pendant		Handheld
SK-910RBQ	SK-917T1-GBQ	SK-919T1-GBQ	SK-919TP1H-BQ
	SK-917T1-GBUQ	SK-919T1-GBUQ	
SK-910RB2Q	SK-917T2-GNQ	SK-919T2-GNQ	SK-919TP2H-NQ
	SK-917T3-GNQ	SK-919T3-GNQ	SK-919TP4H-NQ
	SK-917T4-GNQ	SK-919T4-GNQ	
433.92MHz Pendant 68 Billion codes			
SK-910R-4Q	SK-939T1-GBQ		
	SK-939T1-GBUQ		
SK-910R2-4Q	SK-939T2-GNQ		
	SK-939T3-GNQ		
	SK-939T4-GNQ		

SECO-LARM® U.S.A., Inc.

16842 Millikan Avenue, Irvine, CA 92606

Phone: (949) 261-2999 | (800) 662-0800 Fax: (949) 261-7326

Website: www.seco-larm.com Email: sales@seco-larm.com



Three and Four-Channel RF Receivers

- SK-910R3Q** 315MHz, 3 Channel
- SK-910R4Q** 315MHz, 4 Channel
- SK-910R4-4Q** 433.92MHz, 4 Channel*

Features:

- Four programmable relay output modes:
 - Momentary (1, 2, 3, 4, 5, 10, 30, or 60 seconds)
 - Toggle (ON/OFF)
 - Latch
 - Validity
- 11~24 VAC/VDC Operation
- Range: Up to 500ft (152m)†
- Controls garage doors, gates, house lights, alarm panels or other devices via remote
- LED indicates RF reception, learn mode entered, transmitter learned, memory cleared, and relay output mode
- Pushbutton programming, no need to cut jumpers
- Up to 15 transmitter button codes can be learned



SK-910R3Q



SK-910R4Q

4
Output modes

11~24
VAC/VDC

LED
Indicators

Up to
500ft

Specifications:

Model	SK-910R3Q	SK-910R4Q	SK-910R4-4Q
Operating frequency	315MHz	433.92MHz	
Memory capacity	15 transmitter button codes per channel		
Operating voltage	11~24 VAC/VDC		
Operating current	Standby	12mA@12VDC	
	Active	50mA@12VDC per channel	
Relay contact rating	Form C 10A@24VDC per channel		
Connectors	Screw terminals, +, -, with NO/NC/COM per channel		
Dimensions	3 1/8" x 2 9/16" x 1" (80x65x25 mm)		

*Special order item. Contact SECO-LARM for more details.
 †Operating range will vary greatly depending on the installation and operating environment.

Compatible Transmitters:

Model	315MHz		
	CODEBUMP™	68 Billion Codes	
	Pendant		Handheld
SK-910R3Q	SK-917T1-GBQ	SK-919T1-GBQ	SK-919TP1H-BQ SK-919TP2H-NQ SK-919TP4H-NQ
	SK-917T1-GBUQ	SK-919T1-GBUQ	
	SK-917T2-GNQ	SK-919T2-GNQ	
SK-910R4Q	SK-917T3-GNQ	SK-919T3-GNQ	SK-919TP4H-NQ
	SK-917T4-GNQ	SK-919T4-GNQ	
	433.92MHz Pendant 68 Billion codes		
SK-910R4-4Q	SK-939T1-GBQ		
	SK-939T1-GBUQ		
	SK-939T2-GNQ		
	SK-939T3-GNQ SK-939T4-GNQ		

SECO-LARM® U.S.A., Inc.

16842 Millikan Avenue, Irvine, CA 92606
 Phone: (949) 261-2999 | (800) 662-0800 Fax: (949) 261-7326
 Website: www.seco-larm.com Email: sales@seco-larm.com

