

2-Channel RF Transmitters and Receiver

Please visit the SECO-LARM website www.seco-larm.com for complete installation instructions.

Please read the manual before you begin the installation.

SK-919TD2A-UP 2-Button Pre-Coded Transmitter

SK-917T2A-UQ 2-Button CODEBUMP™ Transmitter

- Range: Up to 500ft (152m)*, 315MHz
- LED Transmission indicator
- Includes 12VDC alkaline battery
- Compatible with all 315MHz SECO-LARM receivers
- SK-919TD2A-UP: 68 billion possible codes
- SK-917T2A-UQ: 18 quintillion possible codes



SK-919TD2A-UP



SK-919TP2H-NUQ

SK-919TP2H-NUQ 2-Button Handheld Transmitter

- Range: Up to 500ft (152m)*, 315MHz
- Over 68 billion possible codes
- Includes two 3VDC lithium batteries
- Compatible with all 315MHz SECO-LARM receivers
- Visor clip and belt clip included. Belt-clip holster and wall-mount bracket also available (model #: SK-9HBC)
- Low battery indicator – LED flashes when battery drops below 2VDC




SK-910RB2Q

SK-910RB2Q 2-Channel Receiver

- Five programmable relay output modes:
 - 4-Second momentary
 - 1-Second momentary
 - Toggle (ON/OFF)
 - Latch
 - Validity
- 11~24 VAC/VDC Operation
- Range: Up to 500ft (152m)*, 315MHz
- Independently programmable outputs
- Controls garage doors, gates, house lights, alarm panels or other devices via remote
- Two LEDs indicate RF reception, learn mode entered, transmitter learned, memory cleared, and relay output mode
- Pushbutton programming, no need to cut jumpers
- Up to 15 transmitter button codes per channel can be learned
- Compatible with all 315MHz SECO-LARM transmitters

Also Available from SECO-LARM®:

SK-91ERSD	
Increase range up to 1,000ft (304m)* with the Extended Range Antenna	

SK-910RB2Q Specifications:

Operating frequency		315MHz
Memory capacity		15 Transmitter button codes per channel, 30 total
Operating voltage		11~24 VAC/VDC
Operating current	Standby	8mA@12VDC
	Active	30mA@12VDC
Relay output modes		4-Sec momentary, 1-sec momentary, toggle, latch, validity
Relay contact rating		Form C 10A@24VDC
Connectors		Screw terminals: Power (+,-) 1 relay per channel (NO/NC/COM)
Dimensions		3 7/16" x 3 7/16" x 1 1/8" (87x87x28 mm)

*Actual range will vary greatly depending on the installation and operating environment

SECO-LARM® U.S.A., Inc.

16842 Millikan Avenue, Irvine, CA 92606

Phone: (949) 261-2999 | (800) 662-0800 Fax: (949) 261-7326

Website: www.seco-larm.com Email: sales@seco-larm.com



Copyright © 2019 SECO-LARM U.S.A., Inc. All rights reserved. All trademarks are the property of SECO-LARM U.S.A., Inc. or their respective owners. The SECO-LARM policy is one of continual development. For that reason, SECO-LARM reserves the right to change prices and specifications without notice. SECO-LARM is not responsible for misprints.

SECO-LARM® ENFORCER® CRIMEBUSTER® CBA® SLI®

PI_SK-910RB2Q_190211_ML.docx

Transmisores y Receptores RF de Dos Canales

Por favor visite el sitio web de SECO-LARM www.seco-larm.com para obtener instrucciones de instalación completas.

Por favor lea el manual antes de usar el equipo.

SK-919TD2A-UP Transmisor pre-codificado en fábrica

SK-917T2A-UQ Transmisor CODEBUMP™

- Alcance de 500 pies (152m), 315MHz
- LED indicador de transmisión
- Incluye batería alcalina 12VCC
- Dos botones, tres canales
- SK-919TD2A-UP: 68 mil millones códigos posibles
- SK-917T2A-UQ: 18 quintillón códigos posibles



SK-919TD2A-UP



SK-919TP2H-NUQ

SK-919TP2H-NUQ Transmisor portátil de dos botones

- Alcance de 500 pies (152m), 315MHz
- Alrededor 68 mil millones (6.8x10¹⁰) códigos posibles
- Incluye dos 3V C.C. baterías de litio
- Compatible con todos los 315MHz SECO-LARM receptores
- Clip de visera y clip de cinta incluido. Funda del clip de cinta & corchete para montar en pared también disponible (Modelo: SK-9HBC)
- Dos botones, tres canales



SK-910RB2Q

SK-910RB2Q

Receptor de dos canales

- Cinco modos de salida programables:
 - 4-Segundos de momentáneo
 - Segundos de momentáneo
 - Salida de toggle
 - Salida de latch
 - Salida de validad
- Flexible voltaje de operación: 11~24VCA / VCC
- Rango hasta 500 pies (152m), 315MHz
- Canales independientemente programables
- Controla garages, puertas, luces de casa, paneles de alarmas, y otros mecanismos vía control remoto
- LED indica recepción RF, ingreso del modo de aprendizaje, aprendizaje del transmisor, memoria borrada, y modo de salida
- Programación de dos botones, ninguna necesita de cortar alambres
- Compatible con todos los transmisores de 315MHz de SECO-LARM (código fijo y CODEBUMP™)

Ahora disponible desde **SECO-LARM®**:

SK-91ERSD

Aumente el rango hasta 1,000 pies (304m)* con antena de rango extendido



Especificaciones del SK-910RB2Q:

Frecuencia operando	315MHz	
Capacidad de memoria	15 códigos de botón del transmisor por canal, 30 por receptor	
Voltaje operando	11~24 VCA/VCC	
Corriente	Destellando	8mA@12VCC
	Activado	30mA@12VCC
Modos de salida	4-seg. momentáneo, toggle, latch, validad, 1-seg. momentáneo	
Calificación de contacto del relevador	Forma C 10A@24VCC	
Conectores	Terminales para atomillar: Alimentación (+,-) 2 relevadores (NA/NC/COM)	
Dimensiones	3 7/16" x 3 7/16" x 1 1/8" (87x87x28 mm)	

* El rango de operación (cambia bastante/ varía mucho) dependiendo de la instalación y el ambiente operativo

SECO-LARM® U.S.A., Inc.

16842 Millikan Avenue, Irvine, CA 92606

Phone: (949) 261-2999 | (800) 662-0800 Fax: (949) 261-7326

Website: www.seco-larm.com Email: sales@seco-larm.com