

# **Data Distributor**

# **RD-304-D1Q**

The ENFORCER RD-304-D1Q RS-485 Data Distributor transmits two (2) RS-485 control signals to four (4) RS-485 outputs. The Data Distributor can be used with any RS-485 controlled camera, and can control up to 64 RS-485 controlled cameras by using multiple units in a daisy-chain configuration.

#### Features:

- ► Range: Up to 4,000' (1,200m)
- ▶ Connect up to 64 RS-485 cameras or devices
- ▶ Inputs: RS-485 and RS-232
- Outputs: Four (4) RS-485
- 12VDC power adapter (included)
- Mounting bracket and rubber feet included
- ► Built-in surge protection
- ▶ Built-in signal isolation
- Dual colored LED:

Red - RS-485 or RS-232 activity


Blue - Power ON

## **Specifications:**

Max. number of inputs		Two (2)
Input connectors		One (1) RS-232 / two (2) RS-485
Output		Four (4) RS-485 terminal blocks
Power supply		12VDC 500mA adapter (included)
Current draw		350mA
LED	Blue	Power ON
Indicators	Red	RS-485 activity
Operating temp.		32° ~ 113° F (0° ~ 45° C)
Dimensions		4 <sup>3</sup> / <sub>8</sub> " x 3 <sup>3</sup> / <sub>4</sub> " x 1 <sup>1</sup> / <sub>8</sub> " (111 x 95 x 29 mm)
Weight		15 oz. (425g)
Material		Metal



### **Sample Application:**



Copyright 2009 SECO-LARM U.S.A., Inc. All rights Reserved.
The SECO-LARM policy is one of continual development. For that reason SECO-LARM reserves the right to change prices and specifications without notice. SECO-LARM is not responsible for misprints.





Tel: 1-800-662-0800 (Domestic U.S. & Canada)
Tel: 1-949-261-2999 (California and International)

Email: info@seco-larm.com Fax: 1-949-261-7326 Website: www.seco-larm.com

