

VGA-to-HDMI Converter with Scaler



MVA-VH01Q

The MVA-VH01Q VGA-to-HDMI Converter with Scaler allows the user to convert video from VGA devices on HDMI displays. Active operation allows the conversion of formats as large as 1920x1080. The MVA-VH01Q also has a 3.5mm stereo input allowing the conversion of audio as well.




Features:

- Converts VGA + Audio to 720p or 1080p HDMI
- Supports input resolutions up to 1920x1080
- Supports up to 1080p on HDMI output
- Stereo audio input
- Switch for switching between 720p and 1080p upscaling
- Plug and play operation

Specifications:

Input resolution	640x480, 800x600, 1024x768, 1280x720, 1280x768, 1280x800, 1280x960, 1280x1024, 1360x768, 1440x900, 1600x1200, 1920x1080
Output resolution	720p, 1080p
Video input signal	3.3V
DDC Input signal	5V
Vertical frequency	60Hz
Video amplifier bandwidth	1.65Gbps/165MHz
Power supply	5VDC (USB)
Operating temperature	32°~158° F (0°~70° C)
Operating humidity	5%~95% RH (no condensation)
Dimensions	2 ³ / ₈ " x 2 ¹ / ₈ " x 1 ³ / ₁₆ " (60x54x20 mm)
Weight	1.4oz (40g)

Dimensions:



SECO-LARM® U.S.A., Inc.

16842 Millikan Avenue, Irvine, CA 92606

Phone: (949) 261-2999 | (800) 662-0800 Fax: (949) 261-7326

Website: www.seco-larm.com Email: sales@seco-larm.com



Copyright 2016 © SECO-LARM U.S.A., Inc. All rights reserved. All trademarks are the property of SECO-LARM U.S.A., Inc. or their respective owners. The SECO-LARM policy is one of continual development. For that reason, SECO-LARM reserves the right to change prices and specifications without notice. SECO-LARM is not responsible for misprints.

SECO-LARM® ENFORCER® CRIMEBUSTER® CBA SLI®

Pi_MVA-VH01Q_160628.docx