

## 2-Channel RF Transmitter & Receiver, 433.92MHz

### SK-939TS2A-PQ Two-Button Pendant Transmitter

- 433.92MHz
- 68 Billion possible codes
- Two buttons, three channels
- LED transmission indicator
- Includes 12VDC alkaline battery

SK-939TS2A-PQ



### SK-910R2-4Q Two-Channel Receiver

- 433.92MHz
- Four programmable relay output modes:
  - 4-Second Momentary Output
  - Validity Output
  - Toggle Output
  - 1-Second Momentary Output
- Flexible operating voltage: 11~24 VAC/VDC
- Learns up to 15 transmitter button codes per channel (a total of 30 per receiver)
- Two independently programmable channels
- Controls garage doors, gates, house lights, alarm panels, or other devices via remote
- Compatible with SK-939TS2A-PQ and all other 433.92MHz SECO-LARM transmitters
- Two LEDs indicate RF reception, learn mode entered, transmitter learned, memory cleared, and relay output mode for each channel

Two independently programmable channels with 4 output modes

SK-910R2-4Q



### SK-910R2-4Q Specifications:

Operating frequency	433.92MHz	
Memory capacity	15 transmitter button codes per channel, 30 per receiver	
Operating voltage	11~24 VAC/VDC	
Operating current	Standby	8mA@12VDC
	Active	30mA@12VDC per channel
Relay output modes	4-sec. momentary, toggle, validity, 1-sec. momentary	
Relay contact rating	Form C 10A@24VDC or 120VAC per channel	
Connectors	Screw terminals: Power (+,-) 2 relays (NO/NC/COM)	
Dimensions	3/16"x3/16"x1 1/8" (87x87x28 mm)	

### Also Available from SECO-LARM®:

#### SK-93ERSD

Increase range with the Extended Range Antenna. Antenna plugs directly into SK-910R2-4Q with 9ft connection cable.



### SECO-LARM® U.S.A., Inc.

16842 Millikan Avenue, Irvine, CA 92606

Phone: (949) 261-2999 | (800) 662-0800 Fax: (949) 261-7326

Website: [www.seco-larm.com](http://www.seco-larm.com) Email: [sales@seco-larm.com](mailto:sales@seco-larm.com)



Copyright © 2017 SECO-LARM U.S.A., Inc. All rights reserved. All trademarks are the property of SECO-LARM U.S.A., Inc. or their respective owners. The SECO-LARM policy is one of continual development. For that reason, SECO-LARM reserves the right to change specifications without notice. SECO-LARM is not responsible for misprints.

SECO-LARM® ENFORCER® CRIMEBUSTER® CBA SLI®