

Desktop and Footswitch RF Wireless Transmitters

SK-919TP2D-P – 2-Button Desktop Transmitter

SK-919TP2D-F – 2-Button Footswitch Transmitter

- ▶ RF remote controlled activation of locks, cameras or other devices from the convenience of a desk or other location.
- ▶ Operates up to 500 feet (160m).
- ▶ Use in offices, factories, institutions or residences.
- ▶ Portable - easily move from one location to another, or mount to a wall.
- ▶ Attractive heavy-duty aluminum case. Fits decor of any room.
- ▶ Large buttons for easy use.
- ▶ Small size: 6¼" x 4¾" x 2¼" (159 x 121 x 58 mm). Place on any desktop.
- ▶ LED indicators for transmission, low battery, and battery charging.
- ▶ Rechargeable 9-volt battery and power supply included.
- ▶ Compatible with all SECO-LARM receivers.



SK-919TP2D-P



SK-919TP2D-F

Specifications:

SK-919TP2D-P

SK-919TP2D-F

| | | |
|---------------------|---|---|
| Number of Buttons | 2 | 2 |
| Number of Channels | 3 | 3 |
| Operating Frequency | 315MHz | |
| Operating Voltage | 9VDC (rechargeable Nickel Metal Hydride battery included) | |
| Operating Current | 100uA @ 9VDC (standby) 10mA @ 9VDC (activated) 17mA max. charge current for ST-1212-U0.5A | |
| Dimensions | 6¼" x 4¾" x 2¼" (159 x 121 x 58 mm) | |