

Wireless Vibrating Receiver

RA-4961-VPQ

Wireless Vibrating Receiver

Features:

- Functions similar to that of the RA-4961Q
- Connect up to 4 wireless transmitter accessories
- Audible, visual, and physical alert via built-in speaker, LEDs and vibration
- Belt clip and small size for easy portability
- Each channel independently programmable



RA-4961-VPQ

Specifications:

Model Number		RA-4961-VPQ
Frequency		914.8MHz
Channels		4
Power supply		2x AA Batteries (Not Included)
Current Draw	Standby	1mA
	Max	80mA
Estimated battery life		60 days (3 triggers/day)
Receiver low battery indicator		Receiver beeps every 5 seconds
Accessory low battery indicator		Zone LED for accessory blinks
Sound level (dB)		76dB@1ft(30cm)
IP rating		IP 30
Operating Temperature		32°~140°F (0°~60°C)
Dimensions		2 ⁹ /16"x1 ¹ /16"x3 ⁹ /16" (65x27x91mm)
Weight (without batteries)		2.7-oz (78g)

*Line of sight. Transmission range will vary depending on installation and operating environment.



16842 Millikan Avenue, Irvine, CA 92606

Phone: (949) 261-2999 | (800) 662-0800 Fax: (949) 261-7326 Website: www.seco-larm.com Email: sales@seco-larm.com

All trademarks are the property of SECO-LARM U.S.A., Inc. or their respective owners. The SECO-LARM policy is one of continual development. For that reason, SECO-LARM reserves the right to change prices and specifications without notice. SECO-LARM is not responsible for misprints.



Copyright 2015 © SECO-LARM U.S.A., Inc. All rights reserved.