

HD 4-in-1 Surge Protector

VS-1V12YQ

The ENFORCER HD 4-in-1 Surge Protector is a passive device that helps protect sensitive HD and Analog CCTV equipment from power surges. The device can be deployed in new installations or existing ones.

Features:


- Helps prevent damage to sensitive HD-TVI, HD-CVI, HD-AHD, and Analog CCTV cameras, DVRs, and switches
- Intercepts repeated surges and spikes that could damage HD-TVI, HD-CVI, HD-AHD, and Analog CCTV equipment
- Passive operation – no external power required
- Includes a 16" grounding wire for convenient connection to ground

Specifications:

Bandwidth	Up to 270MHz	
Maximum input	6Vp-p	
Insertion loss	0.8dB@42MHz	
Return loss	16dB	
Frequency response	Up to 3dB@10MHz	
Insulation resistance	10,000MΩ	
Maximum surge voltage	4kV	
Discharging current	15kV	
Surge life	300 surges@200A	
Surge reaction speed	<1ns	
Surge resistance	0Ω	
Signal passing capability	Breakdown voltage	6V
	Clamping voltage	25V
Connector	In	BNC Male (75Ω)
	Out	BNC Female (75Ω)
Impedance	~75Ω (BNC-to-BNC)	
Dimensions	3 1/8" x 1" x 1" (79x25x25 mm)	
Cable length	15 3/4" (400mm)	
Weight	2.3-oz (65g)	
Material	Aluminum	
Operating temperature	-40°~194° F (-40°~90° C)	



Dimensions:



Also available from SECO-LARM:

HD-SDI Surge Protector
VS-1V22AQ



IP Surge Protector
IPV-PD88Q



PoE Surge Protector
IPV-P188Q



HDMI Surge Protector
VS-1AHHAQ



SECO-LARM® U.S.A., Inc.

16842 Millikan Avenue, Irvine, CA, 92606

Phone: (949) 261-2999 | (800) 662-0800 Fax: (949) 261-7326

Website: www.seco-larm.com Email: sales@seco-larm.com



Copyright © 2016 SECO-LARM U.S.A., Inc. All rights reserved. The SECO-LARM policy is one of continual development. For that reason, SECO-LARM reserves the right to change prices and specifications without notice. SECO-LARM is not responsible for misprints. SECO-LARM® ENFORCER® CRIMEBUSTER® CBA SLI®

PI_VS-1V12YQ_161115.docx