

Wave-to-Open Sensor

SD-927PWCQ Single-gang, White plastic faceplate

The ENFORCER Wave-to-Open Sensor uses IR technology to request egress from a protected area or activate a device with the simple wave of a hand. Since no touch is required, this sensor is suitable for use in hospitals, clinics, labs, cleanrooms (to reduce the risk of contamination), schools, factories, or offices.

Features:

- Range up to 2" (5cm)
- White plastic single-gang plate
- 3A relay, triggers minimum 0.5 sec or as long as hand is near the sensor
- Quick connect screw-less terminal block
- LED illuminated sensor area for easy identification.
- Selectable LED colors (turns from red to green or green to red) to show sensor activated.



SD-927PWCQ

12 VDC








Specifications:

		,	
Operating voltage		12VDC	
Current draw (max.)		50mA@12VDC	
Relay type		Form C dry contact, 3A@30VDC	
Response time		10ms	
LEDS	Standby	Red*	
LEDS	Triggered	Green*	
Output time		Minimum 0.5 sec or as long as hand is near the sensor	
Sensing range		2" (5cm)	
Operating temperature		-4°~131° F (-20°~55° C)	
Dimensions		2 ³ / ₄ "x 4 ¹ / ₂ "x1 ¹ / ₈ " (70x 115x29 mm)	
Weight		2.5-oz (70g)	

Dimensions:



SECO-LARM® U.S.A., Inc.

16842 Millikan Avenue, Irvine, CA 92606

Phone: (949) 261-2999 | (800) 662-0800 **Fax:** (949) 261-7326 **Website:** www.seco-larm.com **Email:** sales@seco-larm.com

Copyright © 2020 SECO-LARM U.S.A, Inc. All rights reserved.

All trademarks are the property of SECO-LARM U.S.A., Inc. or their respective owners.

The SECO-LARM policy is one of continual development. For that reason, SECO-LARM reserves the right to change prices and specifications without notice. SECO-LARM is not responsible for misprints.

^{*}Default, reversible by jumper

Ordering Information:

Wave-to-Open Sensors						
Model	SD-927PWCQ	SD-927PKC-NEQ	SD-927PKC-NFQ	SD-927PKC-NSQ		
Language	English, French, and Spanish Decals	English	French	Spanish		
Photo	© ENFORCER*	WAVE TO OPEN	SORTIE SANS CONTACT	SALIDA SIN TOCAR		

Wave-to-Open Sensors with Override Button						
Model	SD-927PKC-NEVQ	SD-927PKC-NFVQ	SD-927PKC-NSVQ			
Language	English	French	Spanish			
Photo	WAVE TO OPEN EASTERNEEST	SORTIE PAFEMEEN* MAN CONTACT MANUELLE PAFEMEEN* Commande Manuelle	SALIDA ENFORCEN* SIN TOCAR MARGINETOCAL Operación Margin			

Sensor Only					
Model	CS-PD535-TAQ	CS-PD535-TBQ [†]			
Photo			For our full line of OEM/private label infrared sensors, contact SECO-LARM		
Description	1 ¹ / ₄ " (32mm) Sensor	1 ¹ / ₄ " (32mm) Sensor			

†Special order. Contact SECO-LARM for details



16842 Millikan Avenue, Irvine, CA 92606

Phone: (949) 261-2999 | (800) 662-0800 Fax: (949) 261-7326 Website: www.seco-larm.com Email: sales@seco-larm.com

